


02 Broadcasts

These events are not part of the DQMH default features and have to be added to every HSE DQMH module.

'Module Is Ready'

Use the Module Is Ready broadcast to indicate that a module is ready to be used in the application



'System Message'


Sends a HSE-generic broadcast message, consisting of an Identifier, a variant Payload and Source information.

- Provides a generic way of broadcasting information
- Allows for dynamic registering and triggering of broadcast events


System Message Argument

- string Identifier
- variant Payload
- enum Source Type (module, application, network)
 - the typedef can be found in `hse-libraries/hse-dqmh.lvlib/Templates` and `Controls/System Message Source.ctl`
- 4. string Source Name (Module Name)
 - for clones, the Clone ID is appended to the Module Name

Singleton




Cloneable




Message Types


Add to Run-Time Menu




Get Module Identifier




Ready for Display




Remove from Run-Time Menu




Removed from Subpanel



Startup Completed



Update Splash Screen Message



From:

<https://dokuwiki.hampel-soft.com/> - **HAMPEL SOFTWARE ENGINEERING**

Permanent link:

<https://dokuwiki.hampel-soft.com/kb/labview-frameworks/dqmh/hse-flavour/broadcasts?rev=1786983050>

Last update: **2026/08/17 16:10**

